

HIGH EFFICIENCY DRIVER FOR COLOR LIGHT EMITTING DIODES (LED)

FIELD OF THE INVENTION

This invention relates to the field of power converters, in particular to the field of power converters for Light Emitting Diodes (LED).

BACKGROUND OF THE INVENTION

Among many different types of electrical illuminating devices, Light Emitting Diode (LED) is becoming a popular light source increasing the utility of LEDs for many purposes including illumination. Light emitting diodes producing different colors, such as, red, blue and green LEDs are available. Combinations of these primary colors can produce almost any color enhancing LED use for many decorative lighting applications and illumination. A light emitting diode, being of small size, also has the potential to produce small size illumination apparatus, particularly with special power drivers to efficiently utilize them.

LEDs are well suited for implementing a color pixel in a digital image display by combining several LEDs to generate a range of desired colors at the pixel. In order to drive a color pixel consisting of three light emitting diodes each with one of the primary colors, typically requires three separate power supplies producing different voltage. Controlling these three power supplies separately enables the three LEDs to produce a desired color with a desired brightness. Most LEDs work at low voltages, typically 1.5V to 4 volt. Since red, blue and green LEDs all have different turn on or forward voltages, each of the power supplies must produce current at different voltages. Moreover, often a number of LEDs are connected in parallel in order to increase the brightness, thus requiring the power supply to provide a high enough current to drive the parallel LEDs.

A drawback of low-voltage high current power supplies is their low efficiency. This is because most switching power is supplied across an output diode having a forward voltage comparable to that of the intended LED load. Thus, voltage produced is shared between this diode and the LED and brings

the efficiency down to nearly 50 per cent with the high current producing high resistive losses.

A known method for avoiding the need for low-voltage power supply connects a number of LEDs in series so that the driving voltage is the sum of the voltage of each LED in connected in series. However, this arrangement reduces reliability because the failure of any one of the LEDs in the series arrangement results in the failure of the whole arrangement.

Moreover, it is desirable to have a single power supply rather than three separate ones for the three primary colors. However, as indicated above, LEDs corresponding to the three primary colors correspond to different forward voltage drops. Typically, a linear driver is placed in series with LED of each color while the series connection is connected to a single constant voltage power source. The driver takes up the voltage difference between the power source and the LED. However, this method exhibits great power dissipation and low efficiency. The efficiency of this method is only around 50 per cent as the voltage drop across the driver is often comparable to the forward voltage of the LED. An arrangement with such low efficiency produces significant heat resulting in the need for a heat sink increasing product size while reducing reliability.

SUMMARY OF THE INVENTION

Apparatus and method for providing power to multiple light emitting diodes (LEDs), including those corresponding to the three primary colors, are disclosed. The apparatus provides an integrated solution to drive the three types of color LEDs by using the LED itself as a rectifying device in a switching power converter. Furthermore, the apparatus does not require a dissipative element, e.g., a linear driver resulting in energy efficient operation due to lower dissipation than known power supplies. Various embodiments of the invention provide simple non-isolated power conversion as well as isolated configuration for off-line operation. Consequently, known off-line power converter configuration such as forward and flyback converters are compatible with the disclosed apparatus. The brightness of each of the three

colors can be modulated by a passive element, the duty cycle or the switching frequency resulting in a versatile and highly efficient power conversion apparatus with fewer components and smaller size than known designs.

The disadvantages of known power converters for LEDs are overcome by the embodiments of this invention. This and other advantages of a reliable power supply to drive multiple (typically three) color LEDs in an energy efficient manner by delivering current at low voltage with high efficiency are enabled by embodiments of the invention described in the following detailed description.

BRIEF DESCRIPTION OF DRAWINGS

FIGURE 1 illustrates an embodiment of the invention enabling modulation of the current through less than all of the LEDs.

FIGURE 2 presents exemplary current waveforms corresponding to operations in the discontinuous mode corresponding to the embodiment illustrated in **FIGURE 1**.

FIGURE 3 presents exemplary current waveforms corresponding to operations in the continuous mode corresponding to the embodiment illustrated in **FIGURE 1**.

FIGURE 4 illustrates an alternative embodiment that enables modulation of the current through all of the depicted LEDs.

FIGURE 5 presents exemplary current waveforms corresponding to operations in the discontinuous mode corresponding to the embodiment illustrated in **FIGURE 4**.

FIGURE 6 presents exemplary current waveforms corresponding to operations in the continuous mode corresponding to the embodiment illustrated in **FIGURE 4**.

FIGURE 7 illustrates an alternative embodiment of the invention that allows only two of the three depicted LEDs to emit light at any given time.



FIGURE 8 presents exemplary current waveforms corresponding to operations in the discontinuous mode corresponding to the embodiment illustrated in **FIGURE 7**.

FIGURE 9 presents exemplary current waveforms corresponding to operations in the continuous mode corresponding to the embodiment illustrated in **FIGURE 7**.

FIGURE 10 illustrates yet another embodiment of the invention that allows the brightness of all the LEDs to be modulated.

FIGURE 11 presents exemplary current waveforms corresponding to operations in the discontinuous mode corresponding to the embodiment illustrated in **FIGURE 10**.

FIGURE 12 presents exemplary current waveforms corresponding to operations in the continuous mode corresponding to the embodiment illustrated in **FIGURE 10**.

FIGURE 13 shows an embodiment of the invention comprising a forward converter and isolation between input and output.

FIGURE 14 shows an embodiment of the invention with isolation between input and output and comprising a flyback converter with a coupled inductor.

FIGURE 15 shows an illustrative embodiment of the invention with isolation between input and output and using a center-tapped transformer.

DETAILED DESCRIPTION OF THE INVENTION

The invention is illustrated with the aid of various example and exemplary embodiments. The embodiments are categorized into two types, viz., non-isolated and isolated configurations. Non-isolated configurations do not provide isolation between the input and the output while isolated configurations isolate the input and output through transformers. Non-isolated configurations will be described first followed by isolated configuration.

In each configuration a desired color is generated by combination of three primary colors, although such an arrangement is not required for practicing the invention. Accordingly, each configuration typically has three

LEDs, or three sets of LEDs, producing primary colors blue, red and green. Combinations of different brightness of the colors produced by respective LEDs in a given configuration produce a variety of colors. Brightness of a LED is varied by varying the current through the LED. The described configurations enable modulation of current through the devices to produce various combinations of the primary colors.

Non-isolated configurations

FIGURE 1 illustrates an embodiment of the invention enabling modulation of the current through less than all of the LEDs supplied by the power converter. **FIGURE 1** shows input terminals **5** and **10** (advantageously connected to a DC power source) with input terminal **5**, for instance having positive polarity, coupled to inductor **15** that is in turn coupled to the anode of light-emitting diode LED **20** of one primary color, say red. The cathode of LED **20** is then coupled to switch **25** to complete the circuit with negative terminal **10**. LED **30**, typically but not necessarily providing a different primary color, has its cathode coupled to positive input terminal **5** and its anode coupled to switch **25**. LED **35**, for instance providing the color blue, is coupled directly across input terminals **5** and **10** with its anode coupled to positive terminal **5** and its cathode coupled to negative terminal **10**.

Notably each LED can, without loss of generality, be replaced by a series or parallel combination of various devices that, in combination, provide similar unidirectional current paths.

The embodiment illustrated in **FIGURE 1** operates as described next. Switch **25** turns on and off at a high frequency. When switch **25** is turned on, current rises for a time-period with the same current flowing through LED **20**. When switch **25** is turned off, current through the inductor **25** flows through LED **30**. LED **35** being directly connected across the input experiences a constant current flow through it. The resulting current waveform for each LED is shown in **FIGURE 2**. For suitable combinations of the inductance and the switching frequency, the inductor current does not decrease to zero with the apparatus operating in a continuous mode. Thus, with high enough inductance of inductor **15** or switching frequency of switch **25**, continuous



mode operation results. **FIGURE 3** shows the current waveforms corresponding to the continuous mode operation.

Current waveforms in **FIGURE 2** show the current through the three LEDs in the discontinuous mode. The waveforms are different reflecting the different brightness of each LED. In fact the relative brightness of LED 20 and LED 30 can be shown by the ratio of current

$$\frac{i_{LED20}}{i_{LED30}} = \frac{V_{F30} + V_{in}}{V_{in} - V_{F20}} \quad \text{eqn 1}$$

where V_{in} is the input voltage, V_{F20} , V_{F30} are the respective LED forward voltages. Changing the input voltage V_{in} allows varying the ratio of the current through LEDs 20 and 30. A front-end converter or a variable voltage source provides a variable V_{in} for adjusting the relative brightness to produce different colors.

Current waveforms in **FIGURE 3** show the current through the three LEDs in the continuous mode. The relative brightness of LED 20 and LED 30 can be shown by the ratio of their respective currents:

$$\frac{i_{LED20}}{i_{LED30}} = \frac{1}{1-D} \quad \text{eqn 2}$$

where D is the duty cycle. The current ratio can be adjusted by the duty cycle. This can be coordinated with a variable input voltage enables further color variation.

Current through LED 35 is dependent on the input voltage and the inherent device characteristic since it is coupled to the input terminals. Thus, the disclosed embodiment provides no loss power conversion. There is no requirement for a dissipative element like the familiar linear driver enabling the converter to deliver all, or most of its energy to illumination with high operation efficiency. However, the use of resistors and other dissipative elements is compatible with the disclosed design.

FIGURE 4 illustrates an alternative embodiment that enables modulation of the current through all of the depicted LEDs. The embodiment of **FIGURE 1** depicts one of the LEDs as directly coupled to the input power source and limited input voltage range. In the embodiment shown in **FIGURE 4**, this constraint is removed since the third LED is arranged in series with the

input power source resulting in control over the current through all LEDs. **FIGURE 4** illustrates, in part, a pair of input terminals **50** and **55** coupled to a DC source. Positive terminal **50** is coupled to the anode of LED **60** with its cathode coupled to inductor **65** that is further coupled to the anode of LED **70** producing another color. LED **70** has its cathode coupled to a switch **75**. Next, switch **75** is coupled to negative input terminal **55**. LED **80** capable of producing yet another color is coupled in parallel with the series combination of inductor **65** and LED **70**.

The embodiment shown in **FIGURE 4** operates as follows. Switch **75**, capable of turning on and off at a high frequency, when turned on causes current through inductor **65** to build up. When the switch **75** is turned off, current through inductor **65** flows through LED **80**. **FIGURE 5** shows current waveforms through the three LEDs in the discontinuous mode. If the inductance of inductor **65** or the switching frequency is high enough, the converter operates in the continuous mode and the corresponding current waveforms are shown in **FIGURE 6**.

The average current through the three LEDs **70**, **80**, and **60** respectively shown in **FIGURE 4** in the discontinuous mode is

$$\frac{i_{LED60}}{i_{LED80}} = \frac{V_{F70} + V_{F80}}{V_{in} - V_{F60} - V_{F70}} \quad \text{eqn 3}$$

$$\frac{i_{LED70}}{i_{LED80}} = \frac{V_{F80} + V_{in} - V_{F60}}{V_{in} - V_{F60} - V_{F70}} \quad \text{eqn 4}$$

where V_{in} is the input voltage, V_{F60} , V_{F70} and V_{F80} are the respective LED forward voltages.

Thus, the three currents through the three LEDs can be varied resulting in controlling the brightness by adjusting the input voltage.

Current waveforms in **FIGURE 6** show the current through the three LEDs in the continuous mode. The following equations describe the relative brightness of the LEDs:

$$\frac{i_{LED60}}{i_{LED80}} = \frac{D}{1-D} \quad \text{eqn 5}$$

$$\frac{i_{LED70}}{i_{LED80}} = \frac{1}{D} \quad \text{eqn 6}$$

where D is the duty cycle. Each of the current ratios can be adjusted by varying the duty cycle with further coordination with a variable input voltage to control LED produced color.

FIGURE 7 illustrates an alternative embodiment of the invention that allows only two of the three depicted LEDs to emit light at any given time. **FIGURE 7** illustrates a pair of input terminals **100** and **105** for connecting to a DC power source. Of course, modified alternative designs including rectification and the like would allow other sources of power to serve as input power as well. One or more LED, termed LED **110** is coupled directly across the positive and negative input terminals. LED **110** has brightness dependent on the input voltage and the inherent device characteristic. An inductor **115** coupled to positive terminal **100** is further coupled to the anode of LEDs **120** and **125**. LED **120** has its cathode coupled a switch **130** that is further coupled to the negative terminal **105**. LED **125** also has its cathode coupled to negative terminal **105**. As previously mentioned, LED **125** may be replaced by a plurality of devices connected in series such that the total voltage when activated is higher than the magnitude of the input voltage.

Operation of the embodiment shown in **FIGURE 7** is similar to the previously described embodiments. Briefly, high frequency switch **130** turns on resulting in an increase in the current through inductor **115**. When high frequency switch **130** turns off, the inductor **115** causes current to flow through LED **125**. In this embodiment of the invention, the total voltage drop across LED **125** is higher than the input voltage at terminals **100** and **105**. This arrangement decreases the current through LED **125** after switch **130** turns off. LED current waveforms for discontinuous operation are shown in **FIGURE 8**. As mentioned previously in the context of other embodiments, if the inductance of inductor **115** or switching frequency of switch **130** is high enough the converter may operate in the continuous mode as is shown in **FIGURE 9**.

Equations for currents in the discontinuous mode are shown as follows.

$$\frac{i_{LED120}}{i_{LED125}} = \frac{V_{F125} - V_{in}}{V_{in} - V_{F120}} \quad \text{eqn 7}$$

where V_{in} is the input voltage while V_{F125} and V_{F120} are the respective LED forward voltages. As described earlier, the input voltage allows control over the current ratio.

Current waveforms in **FIGURE 9** show the current through the three LEDs in the continuous mode. The relative brightness of the LEDs is described by the following equation:

$$\frac{i_{LED120}}{i_{LED125}} = \frac{D}{1-D} \quad \text{eqn 8}$$

where D is the duty cycle. The depicted current ratio can be adjusted by the duty cycle and further coordinated with a variable input voltage to modulate the color produced by the LEDs.

FIGURE 10 shows yet another embodiment of the invention that allows the brightness of all the LEDs to be modulated. In contrast to the embodiment illustrated in **FIGURE 7** with two LEDs having variable brightness, **FIGURE 10** enables changing the brightness of all three LEDs. To this end, **FIGURE 10** depicts LED 160 connected in series with the input voltage source to enable control over the current through all of the LEDs as described next.

FIGURE 10 shows input terminals 150 and 155 connected to a DC source. Positive input terminal 150 is coupled to the anode of LED 160 while the cathode of LED 160 is coupled to inductor 165. Inductor 165 is further coupled to cathodes of LEDs 170 and 175. LED 175 is configured such that the total forward voltage is greater than the input voltage plus the forward voltage of LED 160. LED 175 has its cathode coupled to negative input terminal 155. LED 170 has its cathode coupled to a switch 180 which is further coupled to negative input terminal 155.

The embodiment shown in **FIGURE 10** is believed to operate as described next. When high frequency switch 180 turns on current increases through inductor 165 connected in series circuit with LEDs 160 and 170. Turning switch 180 off directs current through inductor 165 and LED 175. Corresponding current waveforms for each of the three depicted LEDs in **FIGURE 10** are shown in **FIGURE 11** for discontinuous mode operation. **FIGURE 12** presents exemplary current waveforms corresponding to

operations in the continuous mode. The average current through the three LEDs in the discontinuous mode can be analyzed as follows:

$$\frac{i_{LED170}}{i_{LED175}} = \frac{V_{F175} - V_{F160} - V_{in}}{V_{in} - V_{F160} - V_{F170}} \quad \text{eqn 9}$$

$$\frac{i_{LED160}}{i_{LED175}} = \frac{V_{F175} - V_{F170} - 2V_{F160}}{V_{in} - V_{F160} - V_{F170}} \quad \text{eqn 10}$$

where V_{in} is the input voltage, V_{F160} , V_{F170} , V_{F175} are the respective forwards voltages corresponding to LED 160, LED 170 and LED 175 respectively. The current ratios can be varied by the input voltage V_{in} .

Current waveforms in **FIGURE 12** show the current through the three LEDs in the continuous mode with the relative brightness of the LEDs described by the following equations:

$$\frac{i_{LED170}}{i_{LED175}} = \frac{D}{1-D} \quad \text{eqn 11}$$

$$\frac{i_{LED160}}{i_{LED175}} = \frac{1}{1-D} \quad \text{eqn 12}$$

where D is the duty cycle. The current ratio can be adjusted by the duty cycle. This can be further coordinated with a variable input voltage to exercise maximum color variation.

As illustrated by the equations above, varying the current through each LED 170, LED 175 and LED 160 allows modulation of its' respective brightness. As is readily noted, changing the duty cycle D and/or the input voltage enables such modulation.

The aforementioned four embodiments provide non-isolated configurations for LEDs producing primary colors, although the configurations are suitable for driving LEDs producing other colors as well.

Isolated configurations

There are three embodiments in this section with one embodiment incorporating the forward type converter, another embodiment incorporating a flyback converter and yet another embodiment depicting use of a center-tap forward converter for driving LEDs.

FIGURE 13 shows an exemplary embodiment of the invention comprising a forward converter. **FIGURE 13** shows power transformer **200** having primary winding **205** and at least one secondary winding **210**. Secondary winding **210** has two terminals **215** and **220**. Terminal **215** is connected to the anode of LED **225** while terminal **220** is coupled to the anode of LED **230**. The cathodes of LEDs **225** and **230** meet at a node that is further coupled to one end of inductor **235**. The other end of inductor **235** connects to the cathode of LED **240** that, in turn, connects via its cathode to terminal **220** to complete the circuit.

Operation of the embodiment illustrated in **FIGURE 13** is described next. Primary winding **205** receives a series of pulses as the primary winding of the transformer of a forward converter, including known forward converters that induce, in response to the pulses at the primary side, alternating voltage pulses at secondary winding **210**. In response to a positive voltage coupled to secondary winding **210**, terminal **215** becomes positive in polarity. This voltage increases the current through inductor **235**, and LEDs **225** and **240**. When the induced voltage is negative then terminal **215** has negative polarity and LED **225** is reverse biased. Then, the current through inductor **235** flows through LED **230** instead of LED **225** in a manner similar to the operation of the embodiment of the invention presented in **FIGURE 4**.

Advantageously, although not as a requirement for practicing the invention, each LED **225**, **230** or **240** produces one of the three primary colors that in combination produce a desired color. Current through any of LEDs **225**, **230** or **240** is modulated to produce a desired brightness with the combination of the three LEDs resulting in a desired color from a broad range of possible colors. The duty cycle and the input voltage determine the current through each of the LEDs **225**, **230** or **240** as described previously in the context of **FIGURE 4**. With no loss of generality it should be noted that each LED is replaceable by a combination of LEDs or other components producing a similar unidirectional current path.

FIGURE 14 shows another exemplary embodiment of the invention comprising a flyback converter with a coupled inductor **250**. Coupled inductor **250** has a primary winding **255**, and multiple secondary windings such as the

shown secondary windings **265**, **270** and **275**. Winding **260** is coupled to LED **280**, winding **265** is coupled to LED **285** and winding **270** is coupled to LED **290**. As described previously, each of the LEDs **280**, **285**, and **290** produce one of the three primary colors that are combined to generate a desired color. In addition, the number of secondary windings can be further varied according to the number of colors required or LEDs driven by the common power converter.

Operation of the embodiment of the invention in **FIGURE 14** is described next with primary winding **255** coupled to a series of alternating square voltage pulses. This apparatus operates as a flyback converter such that when primary winding **255** is energized, LEDs coupled to corresponding secondary windings are reverse biased such that no energy is transferred to them since no current flows through them. When the voltage polarity across winding **255** reverses, energy stored in coupled inductor **250** is released to each LED. In practice this type of converter typically operates in the discontinuous mode when coupled to a front end AC to DC diode-bridge. A series of suitable alternating square voltage pulse for primary winding **255** enable the current drawn from the AC source to follow the alternating voltage to obtain a high power factor.

Brightness of the LEDs can be varied to create different colors combinations as described previously with the currents through the various LEDs depending on the number of turns of the associated secondary winding and the duty cycle.

FIGURE 15 shows another illustrative embodiment of the invention employing a center-tapped transformer. Illustrated center-tapped converter comprises transformer **300** with a primary winding **305**, and secondary windings **310** and **315** coupled together at a node. Secondary winding **310** is coupled to the anode of LED **320** and secondary winding **315** is coupled to the anode of LED **325**. LEDs **320** and **325** have their cathodes connected together and to one end of inductor **330**. Moreover, LED **335** has its anode coupled to inductor **330** and its cathode coupled to the node joining secondary windings **310** and **315**. Advantageously, LEDs **315**, **320** and **335** emit light of

different colors to enable generation of additional colors by combining their respective emissions.

Operation of the embodiment of the invention in **FIGURE 15** is described next. Primary winding **305**, possibly driven by half bridge circuits or full bridge circuits like most forward converters, receives a series of voltage pulses resulting in energizing secondary windings **310** and **315**. Current from secondary windings **310** and **315** flows to inductor **330** via either LED **320** or LED **325** and then to LED **335**. The current through the each of LEDs **320**, **325** and **335** is modulated by varying the ratio of secondary and primary windings, switching frequency, duty cycle, the input voltage, and the value of inductor **330**. Thus, suitably adjusting the current through an LED results in producing a desired brightness and in combination with the color produced by other LEDs generates a desired color.

Although **FIGURES 13-15** include an alternating power source, this is not intended to indicate sinusoidal alternating power sources only. Indeed square waves or even irregular waveforms capable of driving the secondary windings are intended to be included by the illustrative depiction of an alternating power source. The alternating power source includes one or more of a switching forward power converter, a transformer, a switching flyback power converter, a switching bridge power converter, and the like.

The aforementioned embodiments include an inductor coupled in series with a first LED with a second light emitting diode coupled in parallel to the inductor and the first LED. The second LED is oriented so that it is reverse biased when a power source drives a current through the inductor and the first LED. Additionally, a switch controls the connection of the inductor and the first LED to the power source. Furthermore, additional LEDs can be added, for instance a third LED coupled, in parallel to the first light emitting diode, to a first terminal and a second terminal of the power source. Alternatively, a third light emitting diode is coupled in series to the first light emitting diode and to a first terminal and a second terminal of the power source.

Another embodiment comprises an inductor coupled in series with a first LED, a switch controlling a connection of the inductor and the first LED to a power source, in turn, connected in series to the inductor via the switch and a second LED. The second LED has a forward voltage higher than input voltage across the power source and is connected in parallel to the switch and the first LED. To complete the picture, the second LED is coupled in series with the inductor and the power source. As before, additional LEDs can be added, for instance, by using a bank of LEDs instead of a single LED or, for instance, a third light emitting diode coupled in parallel to the first and second input terminals of the power source. The third light emitting diode can also be coupled in series with the first or second terminals of the power source.

If isolation between the input and output side is desired then magnetic coupling is incorporated in the designs. An example apparatus includes a switching forward power converter with a transformer, a secondary winding coupled to the transformer, an LED coupled to the secondary winding and an inductor. Another LED is also connected to the inductor and another terminal of the secondary winding with a third LED coupled in parallel with the series combination of the second light emitting diode and the inductor. The operation of the configuration is as described for FIGURES 13-15.

Another isolation providing design uses a switching flyback power converter, a transformer, a plurality of secondary windings coupled to the transformer, and an LED coupled to the secondary windings. In addition, the apparatus can incorporate a bridge rectifier for converting an alternating current to a direct current with means to operate the flyback converter to operate in discontinuous mode with current delivered by an alternating current source with phase angle following a corresponding alternating voltage.

This is in accordance with the operation of a discontinuous flyback converter. With a fixed duty cycle the input current is proportional to the input voltage making the converter input impedance resistive. If the input voltage is derived from a bridge rectifier driven by a sinusoidal voltage then the input current will also be sinusoidal in phase with the driving voltage. The resulting output LED currents may also be sinusoidal but their brightness variation at line frequency will not be perceived by human eye.

Yet another configuration comprises a switching bridge power converter, a transformer, two or more secondary windings such that a first terminal of the first secondary winding has the opposite polarity to that of a first terminal of the second secondary winding. Two LEDs, coupled together at their cathodes, are connected to an inductor. The anode of the first light emitting diode is connected to the first terminal of the first secondary winding and the anode of the second light emitting diode being connected to the first terminal of the second secondary winding. To complete the design, the inductor coupled to the cathodes of the LEDs is further coupled to a second terminal of the first secondary winding and a second terminal of the second secondary winding via a third light emitting diode.

It will be appreciated that the various features described herein may be used singly or in any combination thereof. Thus, the present invention is not limited to only the embodiments specifically described herein. While the foregoing description and drawings represent an embodiment of the present invention, it will be understood that various additions, modifications, and substitutions may be made therein without departing from the spirit and scope of the present invention as defined in the accompanying claims. In particular, it will be clear to those skilled in the art that the present invention may be embodied in other specific forms, structures, and arrangements, and with other elements, and components, without departing from the spirit or essential characteristics thereof. One skilled in the art will appreciate that the invention may be used with many modifications of structure, arrangement, and components and otherwise, used in the practice of the invention, which are particularly adapted to specific environments and operative requirements without departing from the principles of the present invention. The presently disclosed embodiment is therefore to be considered in all respects as illustrative and not restrictive, the scope of the invention being indicated by the appended claims, and not limited to the foregoing description.